

## On the intrinsic origin of $1/f$ noise

**B. Kaulakys**

Institute of Theoretical Physics and Astronomy, Vilnius University,

A. Goštauto 12, LT-2600 Vilnius, Lithuania and

Faculty of Physics, Vilnius University, Saulėtekio al. 9, LT-2040 Vilnius, Lithuania

### Abstract

The problem of the intrinsic origin of  $1/f$  noise is considered. Currents and signals consisting of a sequence of pulses are analysed. It is shown that intrinsic origin of  $1/f$  noise is a random walk of the average time between subsequent pulses of the pulse sequence, or interevent time. This results in the long-memory process for the pulse occurrence time and in  $1/f$  type power spectrum of the signal.

## 1 Introduction

Ubiquitous of signals and processes with  $1/f$  power spectral density at low frequencies has led to speculations that there might exist some generic mechanism underlying production of  $1/f$  noise. The generic origins of two popular noises: white noise (no correlation in time,  $S(f) \propto 1/f^0$ ) and Brownian noise (no correlation between increments,  $S(f) \propto 1/f^2$ ) are very well known. It should be noted, that Brownian motion is the integral of white noise and that operation of integration of the signal increases the exponent by 2 while the inverse operation of differentiation decreases it by 2. Therefore,  $1/f$  noise can not be obtained by simple procedure of integration or differentiation of the convenient signals. There are no simple, even stochastic, equations generating signals with  $1/f$  noise. Note in this context also to the concept of the fractional Brownian motion and to the half-integration of a white noise signals used for generation of processes with  $1/f$  noise [1]. These and similar mathematical algorithms, procedures and models for generation of the processes with  $1/f$  noise [2, 3] are, however, sufficiently specific, formal or unphysical. They can not, as a rule, be solved analytically and they do not reveal the origin as well as the necessary and sufficient conditions for appearance of  $1/f$  type fluctuations. Physical models of  $1/f$  noise in some physical systems are usually very specialized, complicated and they do not explain the internal origin of the omnipresent processes with  $1/f^\delta$  spectrum.

A lot of contributions are available in the literature concerning the origin of  $1/f$  noise. On the web (<http://linkage.rockefeller.edu/wli/1fnoise>), Wentain Li is collective bibliography of flicker noise. Sufficiently comprehensive bibliography of the contributions concerning the modeling of  $1/f$  noise may be find in references [3–7].

This work is a continuation of series of papers devoted to the modeling  $1/f$  noise in simple systems [4,5] and search of necessary conditions for appearance of the signals with power spectrum at low frequencies like  $S(f) \propto 1/f^\delta$  ( $\delta \simeq 1$ ) [6–9]. In papers [4,5] an analysis of the necessary conditions for appearance of  $1/f$  type fluctuations in the simple systems consisting of few or even one particle and affected by random perturbations is presented. Later, a simple analytically solvable model of  $1/f$  noise has been proposed [6], analyzed [7] and generalized [8]. The model reveals main features, and parameter dependencies of the power spectrum of  $1/f$  noise.

Here considering signals and currents as consisting of pulses generalizations and development of the model [6] are presented. The paper includes derivation of the expression for the correlation function, analysis of the examples of different signals and exhibition of the necessary conditions for appearance of  $1/f$  type power spectrum in the signals consisting of pulses. It is shown that intrinsic origin of  $1/f$  noise is a Brownian motion of the pulse interevent time.

## 2 The model

Let us consider currents or signals represented as sequences of random (but correlated) pulses  $A_k(t - t_k)$ . Function  $A_k(t - t_k)$  represents the shape of the  $k$ -pulse of the signal in the region of the pulse occurrence time  $t_k$ . The signal or intensity of the current of particles in some space cross section may, therefore, be expressed as

$$I(t) = \sum_k A_k(t - t_k). \quad (1)$$

It is easy to show that the shapes of the pulses mainly influence the high frequency,  $f \geq \Delta t_p$  with  $\Delta t_p$  being the characteristic pulse length, power spectrum while fluctuations of the pulse amplitudes result, as a rule, in the white or Lorentzian but not  $1/f$  noise [10]. Therefore, we restrict our analysis to the noise due to the correlations between the pulse occurrence times  $t_k$ . In such an approach we can replace the function  $A_k(t - t_k)$  by  $a\delta(t - t_k)$ . Here  $\delta(t - t_k)$  is the Dirac delta function,  $a = \langle \int_{-\infty}^{+\infty} A_k(t - t_k) dt \rangle$  is the average area of the pulse and the brackets  $\langle \dots \rangle$  denote the averaging over realizations of the process. In such an approach the signal (1) may be expressed as

$$I(t) = a \sum_k \delta(t - t_k). \quad (2)$$

This model also corresponds to the flow of identical point objects: electrons, photons, cars and so on. On the other hand, fluctuations of the amplitudes  $A_k$  may result in the additional noise but can not reduce  $1/f$  noise we are looking for.

## 2.1 Power spectrum

Power spectral density of the signal  $I(t)$  is

$$S(f) = \lim_{T \rightarrow \infty} \left\langle \frac{2}{T} \left| \int_{t_i}^{t_f} I(t) e^{-i2\pi f t} dt \right|^2 \right\rangle \quad (3)$$

where  $T = t_f - t_i$  is the observation time.

We can also introduce the autocorrelation function

$$\Phi(s) = \left\langle \frac{1}{T} \int_{t_i}^{t_f-s} I(t) I(t+s) dt \right\rangle \quad (4)$$

and use the Wiener-Khintchine relations:

$$S(f) = 4 \lim_{T \rightarrow \infty} \int_0^T \Phi(s) \cos(2\pi f s) ds, \quad (5)$$

$$\Phi(s) = \int_0^\infty S(f) \cos(2\pi f s) df.$$

Substitution of Eq. (2) into Eq. (3) results the power spectral density of the signal expressed as sequence of pulses

$$\begin{aligned} S(f) &= \lim_{T \rightarrow \infty} \left\langle \frac{2a^2}{T} \left| \sum_{k=k_{\min}}^{k_{\max}} e^{-i2\pi f t_k} \right|^2 \right\rangle \\ &= \lim_{T \rightarrow \infty} \left\langle \frac{2a^2}{T} \sum_{k=k_{\min}}^{k_{\max}} \sum_{q=k_{\min}-k}^{k_{\max}-k} e^{i2\pi f \Delta(k;q)} \right\rangle \end{aligned} \quad (6)$$

where  $\Delta(k;q) \equiv t_{k+q} - t_k$  is the difference of pulse occurrence times  $t_{k+q}$  and  $t_k$  while  $k_{\min}$  and  $k_{\max}$  are minimal and maximal values of index  $k$  in the interval of observation  $T = t_f - t_i$ .

For a stationary process Eq. (6) yields

$$S(f) = \frac{2a^2}{T} \sum_{q=-N}^N (N+1-|q|) \langle e^{i2\pi f \Delta(q)} \rangle.$$

Here  $N = k_{\max} - k_{\min}$ , the brackets  $\langle \dots \rangle$  denote the averaging over realizations of the process and over the time (index  $k$ ) and a definition  $\Delta(q) = -\Delta(-q) = \Delta(k;q)$  is introduced. For abbreviation of the equations we have omitted the mark of the limit " $\lim_{T \rightarrow \infty}$ " here and further on in expressions for the power spectrum  $S(f)$ .

The average over the distribution of  $\Delta(q)$  may be expressed as

$$\begin{aligned}\langle e^{i2\pi f \Delta(q)} \rangle &\equiv \int_{-\infty}^{+\infty} e^{i2\pi f \Delta(q)} \Psi_{\Delta}(\Delta(q)) d\Delta(q) \\ &= \chi_{\Delta(q)}(2\pi f).\end{aligned}$$

Here  $\Psi_{\Delta}(\Delta(q))$  is the distribution density of  $\Delta(q)$ , and  $\chi_{\Delta(q)}(2\pi f)$  is the characteristic function of the distribution  $\Psi_{\Delta}(\Delta(q))$ . Therefore

$$S(f) = 2a^2 \sum_{q=-N}^N \left( \bar{\nu} - \frac{|q|}{T} \right) \chi_{\Delta(q)}(2\pi f) \quad (7)$$

where  $\bar{\nu} = \left\langle \lim_{T \rightarrow \infty} \frac{N+1}{T} \right\rangle$  is the mean number of pulses per unit time.

When the sum  $\sum_{q=-N}^N |q| \chi_{\Delta(q)}(2\pi f)$  converges and  $T \rightarrow \infty$  we have the power spectrum from Eq. (7) in the form

$$S(f) = 2a\bar{I} \sum_{q=-N}^N \chi_{\Delta(q)}(2\pi f). \quad (8)$$

Here  $\bar{I} \equiv \langle \bar{I}(t) \rangle = \bar{\nu}a$  is the average current.

## 2.2 Correlation function

Substitution of Eq. (2) into Eq. (4) yields the correlation function of the signal (2)

$$\Phi(s) = \left\langle \frac{a^2}{T} \sum_{k,q} \delta(t_{k+q} - t_k - s) \right\rangle.$$

After summation over index  $k$  we have

$$\Phi(s) = \bar{I}a \sum_q \langle \delta(\Delta(q) - s) \rangle$$

where the brackets  $\langle \dots \rangle$  denote again the averaging over realizations of the process and over the time (index  $k$ ), as well. Such averaging coincides with the averaging over the distribution of the time difference  $\Delta(q)$

$$\begin{aligned}\Phi(s) &= \bar{I}a \sum_q \int_{-\infty}^{+\infty} \psi_{\Delta}(\Delta) \delta(\Delta - s) d\Delta \\ \Phi(s) &= \bar{I}a \delta(s) + \bar{I}a \sum_{q \neq 0} \psi_{\Delta}(s).\end{aligned} \quad (9)$$

Here  $\psi_{\Delta}(\Delta)$  is the distribution density of  $\Delta(q)$ . Substitution of Eq. (9) into Eq. (5) yields expressions (7) and (8).

### 3 Examples

Consider some examples of the signals represented by Eq. (2).

(i) Periodic signal expressed as  $I(t) = a \sum_k \delta(t - k\tau)$  generates the power spectrum

$$S(f) = 2a^2 \lim_{T \rightarrow \infty} \frac{\sin^2(\pi(N+1)\tau f)}{T \sin^2(\pi\tau f)} \Rightarrow 2\bar{T}^2 \delta(f), \quad f \ll \tau^{-1}.$$

(ii) Perturbed periodic signal represented by Eq. (2) with the times series expressed as recurrence equations  $t_k - t_{k-1} \equiv \tau_k = \bar{\tau} + \sigma \varepsilon_k$  with  $\{\varepsilon_k\}$  being a sequence of uncorrelated normally distributed random variables with zero expectation and unit variance and  $\sigma$  being the standard deviation of this white noise [5]. For this model we have  $\Delta(q) = q\bar{\tau} + \sigma \sum_{l=k+1}^{k+q} \varepsilon_l$  and the characteristic function

$$\chi_{\Delta(q)}(2\pi f) = e^{i2\pi f \langle \Delta(q) \rangle - \frac{1}{2}(2\pi f)^2 \sigma_\Delta^2} \quad (10)$$

where  $\langle \Delta(q) \rangle = q\bar{\tau}$  and the variance  $\sigma_\Delta^2$  of the time difference  $\Delta(q)$  equals  $\sigma_\Delta^2 \equiv \langle \Delta(q)^2 \rangle - \langle \Delta(q) \rangle^2 = \sigma^2 |q|$ . Substitution of Eq. (10) into Eq. (8) yields the Lorentzian spectrum

$$S(f) = \bar{T}^2 \frac{4\tau_{\text{rel}}}{1 + \tau_{\text{rel}}^2 \omega^2} \quad (11)$$

where  $\omega = 2\pi f$  and  $\tau_{\text{rel}} = \sigma^2/2\bar{\tau}$ .

(iii) Time difference  $\Delta(q) = \sum_{l=k+1}^{k+q} \tau_l$  as a sum of uncorrelated interevent times  $\tau_l$ .

According to Eqs. (6)–(8) we have in this case

$$\begin{aligned} S(f) &= 2a\bar{T} \left[ 1 + 2\text{Re} \sum_{q=1}^N \langle e^{i2\pi f \tau} \rangle^q \right] \\ S(f) &= 2a\bar{T} \left[ 1 + 2\text{Re} \frac{\chi_\tau(\omega)}{1 - \chi_\tau(\omega)} \right]. \end{aligned} \quad (12)$$

For instance, substitution at  $f \ll \bar{\tau}^{-1}$  and  $f \ll \sigma^{-1}$  of Eq. (10) with  $q = 1$  into Eq. (12) results in Eq. (11).

(iv) For the Poisson process

$$\chi_\tau(2\pi f) = \frac{1}{1 - i2\pi f \bar{\tau}}, \quad \text{Re} \frac{\chi_\tau(\omega)}{1 - \chi_\tau(\omega)} = 0$$

and we have from Eq. (12) only the shot noise

$$S(f) = 2a\bar{T} = S_{\text{shot}}. \quad (13)$$

(v) Brownian motion of the interevent time  $\tau_k$  with some restrictions, e.g., with the relaxation to the average value  $\bar{\tau}$ ,

$$\tau_k = \tau_{k-1} - \gamma(\tau_{k-1} - \bar{\tau}) + \sigma \varepsilon_k, \quad (14)$$

when the pulse occurrence times  $t_k$  are expressed as

$$t_k = t_{k-1} + \tau_k. \quad (15)$$

According to Eq. (6) the power spectrum of the signal (2) with the pulse occurrence times  $t_k$  generated by Eqs. (14) and (15) for sufficiently small parameters  $\sigma$  and  $\gamma$  in any desirably wide range of frequencies,  $f_1 = \gamma/\pi\sigma_\tau < f < f_2 = 1/\pi\sigma_\tau$ , is **1/f-like** [6, 7, 8, 9], i.e.,

$$S(f) = \bar{I}^2 \sqrt{\frac{2}{\pi}} \frac{\bar{\tau} \exp(-\bar{\tau}^2/2\sigma_\tau^2)}{\sigma_\tau f}. \quad (16)$$

Here  $\sigma_\tau^2 = \sigma^2/2\gamma$  is the variance of the interevent time  $\tau_k$ .

## 4 Origin of 1/f noise

The origin for appearance of 1/f fluctuations in the model described in Eqs. (14) and (15) is related with the relatively slow, Brownian, fluctuations of the pulse interevent time. For this reason, the variance  $\sigma_\Delta^2$  of the time difference  $\Delta(k; q)$  for  $|q| \ll \gamma^{-1}$  is a quadratic function of the time difference and, consequently, of the difference  $q$  of the pulse serial numbers  $k$  [6, 7, 8, 9], i.e.,

$$\sigma_\Delta^2(k; q) = \sigma_\tau^2(k) q^2. \quad (17)$$

Substitution of Eqs. (10) and (17) into Eq. (8) yields 1/f spectrum (16).

### 4.1 Generalization

For slowly fluctuating interevent time, the time difference  $\Delta(k; q)$  may be expressed as [6, 7, 8, 9]

$$\Delta(q) = \sum_{l=k+1}^{k+q} \tau_l \simeq q\tau \quad (18)$$

where  $\tau = (t_{k+q} - t_k)/q$  is the average interevent time in the time interval  $(t_k, t_{k+q})$ , a slowly fluctuating function of the arguments  $k$  and  $q$ . In such an approach, the power spectrum according to Eq. (6) is

$$S(f) = 2\bar{I}a \sum_q \langle e^{i2\pi f q \tau} \rangle \quad (19)$$

where

$$\langle e^{i2\pi f q \tau} \rangle \equiv \int_{-\infty}^{+\infty} e^{i2\pi f q \tau} \psi_\tau(\tau) d\tau = \chi_\tau(2\pi f q)$$

is the characteristic function of the distribution density  $\psi_\tau(\tau)$  of the interevent time  $\tau$ . Therefore, the power spectrum according to Eq. (19) may be expressed as

$$S(f) \simeq 2\bar{I}^2 \bar{\tau} \Psi_\tau(0) / f. \quad (20)$$

Here the property  $\int_{-\infty}^{+\infty} \chi_\tau(x) dx = 2\pi \Psi_\tau(0)$  of the characteristic function has been used.

## 4.2 Correlation function of $1/f$ noise

The correlation function of  $1/f$  noise in the approximation (18) may be calculated according to Eq. (9), i.e.,

$$\begin{aligned}\Phi(s) &= \bar{I}a \sum_q \int_{-\infty}^{+\infty} \psi_\tau(\tau) \delta(q\tau - s) d\tau \\ &= \bar{I}a \delta(s) + \bar{I}a \sum_{q \neq 0} \psi_\tau\left(\frac{s}{q}\right) \frac{1}{|q|}.\end{aligned}\tag{21}$$

For the Gaussian distribution of the interevent time  $\tau$

$$\psi_\tau(\tau) = \frac{1}{\sqrt{2\pi}\sigma_\tau} \exp\left(-\frac{(\tau - \bar{\tau})^2}{2\sigma_\tau^2}\right)$$

the correlation function (21) reads as

$$\Phi(s) = \frac{\bar{I}a}{\sqrt{2\pi}\sigma_\tau} \sum_q e^{-\frac{(s-q\bar{\tau})^2}{2\sigma_\tau^2 q^2}} \frac{1}{|q|}.\tag{22}$$

It should be noted that the deviation of the variance  $\sigma_\Delta^2$  for large  $q$  from the quadratic dependence (17) and approach to the linear function  $\sigma_\Delta^2 = 2D_{t_k} |q|$  ensures the convergence of sums (21) and (22) and, consequently, results in the Lorentzian power spectrum (11) at  $f \rightarrow 0$  [6, 7, 8, 9]. Here  $D_{t_k}$  is the "diffusion" coefficient of the pulse occurrence time  $t_k$ , related with the variance  $\sigma_{t_k}^2$  of the pulse occurrence time as  $\sigma_{t_k}^2 = 2D_{t_k} k$ . For the model (14)–(15)  $D_{t_k} = \sigma^2/2\gamma^2$ .

The power spectra calculated according to Eq. (5) with the correlation functions (21) and (22) are expressed as Eq. (20) and Eq. (16), respectively.

## 5 Conclusions

From the above analysis we can conclude that *the intrinsic origin of  $1/f$  noise is a Brownian fluctuations of the interevent time of the signal pulses*, similarly to the Brownian fluctuations of the signal amplitude resulting in  $1/f^2$  noise. The random walk of the interevent time in the time axis is a property of the randomly perturbed or complex systems with the elements of selforganization.

## Acknowledgments

The author acknowledges useful discussions with Prof. A. Bastys, Prof. R. Katilius, Prof. A. Matulionis and Dr. T. Meškauskas.

## References

- [1] Mandelbrot, B. B. and Van Ness, J. W., Fractional Brownian motion, fractional noise and applications. *SIAM Rev.*, 1968, 10, 422–437.

- [2] Higuchi, T., Relationship between the fractal dimension and the power law index for a time series: A numerical investigation. *Physica D*, 1990, 46, 254–264.
- [3] Ninness, B., Estimation of  $1/f$  noise. *IEEE Trans. Inform. Theory*, 1998, 44, 32–46.
- [4] Kaulakys, B. and Vektaris, G., Transition to nonchaotic behaviour in randomly driven systems: Intermittency and  $1/f$ -noise. *Proc. 13th Int. Conf. on Noise in Physical Systems and  $1/f$  Fluctuations, Palanga, Lithuania, 1995, Eds. V. Bareikis and R. Katilius*, Singapore: World Scientific, 1995, pp. 677–680.
- [5] Kaulakys, B. and B. Meškauskas, B., On the  $1/f$  fluctuations in the nonlinear systems affected by noise. *Proc. 14th Int. Conf. on Noise in Physical Systems and  $1/f$  Fluctuations, Leuven, Belgium, 1997, Eds. C. Claeys and E. Simoen*, Singapore: World Scientific, 1997, pp. 126–129; adap-org/9806002.
- [6] Kaulakys, B., Simple model of  $1/f$  noise. adap-org/9806004 (1998); Kaulakys, B., Autoregressive model of  $1/f$  noise. *Phys. Lett. A*, 1999, 257, 37–42; adap-org/9907008.
- [7] Kaulakys, B. and Meškauskas, T., Modeling  $1/f$  noise. *Phys. Rev. E*, 1998, 58, 7013–7019; adap-org/9812003.
- [8] Kaulakys, B. and Meškauskas, T., On the generation and origin of  $1/f$  noise. *Nonlinear Analysis: Modelling and Control* (Vilnius), 1999, 4, 87–95.
- [9] Kaulakys, B. and Meškauskas, T., Models for generation of  $1/f$  noise. *Proc. Proc. 15th Int. Conf. on Noise in Physical Systems and  $1/f$  Fluctuations, Hong Kong, 1999, Ed. C. Surya*, 1999, pp.375–378 and *Microel. Reliab.* 2000, 40, 1781–1785; cond-mat/0303603.
- [10] Schick, K. L. and Verveen, A. A.,  $1/f$  noise with a low frequency white noise limit, *Nature*, 1974, 251, 599–601.